

USB-10-4 LVDT Conditioner Unit



The model USB-10-4 is a 4 channel LVDT signal conditioner that operates four LVDTs simultaneously, and converts the reading using 21 bit A to D converter. Four digital readings are displayed on the LCD screen. It can communicate with PC using USB port.

With USB interface there is no need for an external power supply. The maximum interface cable length is 5 meters max. When USB port is disconnected, use an unregulated 5÷12VDC adapter, 250mA max, external power supply. The display has a +/-9.9999 count resolution, with adjustable zero and scale.

- 1÷4 Channels
- 21 bit resolution, at 7 or 800Hz Output Rate
- Software selectable gain and zero adjustment
- Digital filtering and conversion rate
- Software selectable linearization (optional – added upon client request)
- 16x2 alphanumeric characters LCD display
- Programmable multi condition digital limit output (optional – added upon client request)
- USB data communication channel
- Supporting six, five and four wire LVDTs
- Active analog filters (set at the factory according to client request)
- No power supply needed when using USB channel.
- Readout by alphanumeric panel or PC installed software
- Supplied with operating and data collecting software



Specifications

LVDT excitation for every channel

Voltage	3.5 V rms @ 20 mA max
Frequency	1 to 5 kHz, selectable upon request

Signal Input

Input Voltage Range	1V RMS max
Impedance	>100 kΩ

Functions

Zero adjustment	Using PC based software or Front Panel
Gain adjustment	Using PC based software or Front Panel
Resolution	21 bit
Conversion Rate	7 or 800 conversions per second, selected from PC
Non Volatile memory	Flash memory
Low Pass Filtering	Digital filtering > 80 dB, 50 Hz
Readout Display	5 digit (±9.9999 counts)
Serial Communication Port	USB
Serial Protocol	Binary Code (3 Bytesx4channels)
Communication Cable length	,≤ 5m
Power supply	5÷12V DC from adapter when disconnected from USB
Operating temperature range	+5C° to +55°C
Dimension (mm)	125 x 106 x 33
Digital limit output	open collector up to 40V & 50mA (selectable upon request)

How To Order

Ordering example: Model Number: USB-10-4

Rev. A

© Singer Instruments & Control Ltd., 2009

WWW.SINGER-INSTRUMENTS.COM

Information furnished by Singer Instruments & Control is believed to be accurate and reliable. However, no responsibility is assumed by Singer Instruments & Control for its use, nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Singer Instruments & Control Ltd.

Singer Instruments & Control Ltd.

2 Yozma st., Tirat Carmel 39032, ISRAEL
yuval@singer-instruments.com

Tel: 972-4-857-8880
Fax: 972-4-857-8881

540 East Main st., Branford, CT 06405, USA
fred@singer-instruments.com

Tel: 203-481-7278
Fax: 203-488-7190